

Lenovo Go Wireless Mobile Power Bank (10000 mAh)

The **Lenovo Go Wireless Mobile Power Bank (10000 mAh)** takes the hassle out of charging your devices. With the power bank's 10,000 mAh battery handy, you can simultaneously charge up to 30W of devices, 1 via wireless-Qi and 2 via USB-C, with enough power to rapidly restore your device to full battery many times over. That way, you spend less time charging and more time doing what you're best at.



Lenovo
Go

Wireless Power For The Go Generation



Lenovo

Lenovo Go Wireless Mobile Power Bank (10000 mAh)



Thunder Black

Storm Grey

WHY CHOOSE THE LENOVO GO WIRELESS MOBILE POWER BANK (10000 mAh)?



Power Beyond Limitation

In a multi-device workplace, the Lenovo Go Wireless Mobile Power Bank provides immense value to remote workers. Thanks to wireless Qi charging, one power source is all you need to provide up to 15W of wireless power to an unlimited variety of smartphones and mobile devices.



Charging Beyond Expectations

Smart charging technology is the secret behind the Lenovo Go Wireless Mobile Power Bank's ability to intelligently route the available 30W output and charge up to 3 devices simultaneously by wireless and dual USB-C ports.



Portability Beyond Size

The Lenovo Go Wireless Mobile Power Bank goes beyond size and provides a range of innovative portability features. By eliminating the need for multiple cables, supporting simultaneous charging and power pass-through, and providing 10,000 mAh of capacity, remote workers can minimize the hassle of their dynamic work style.

SPECIFICATIONS

PERFORMANCE

| | |
|---------------------------|--|
| Battery | |
| Description | : Lithium Ion Polymer Rechargeable Cell |
| Nominal Capacity | : 10000 mAh (2-cell battery, 5000 mAh) |
| Performance | : 38.5 WHr |
| Recharging Time | : <2 Hours ¹ |
| Input/Output Ports | |
| Input Power | : Suggest 27W (9V/3A) above |
| Output Power | : USB-C : 27W max. (9V/3A, 5V/3A) Wireless : 15W max. |
| Total Output | : 30W max. |
| Charging Connector | : Power-In: 2 x USB-C ² |
| Power-Out | : 2 x USB-C, Qi Wireless |

DESIGN

| | |
|---------------------------------|-------------------------|
| Dimensions (W x D x H) | |
| Packed Dimension | |
| mm | : 221 x 107 x 32 |
| inches | : 8.70" x 4.21" x 1.26" |
| Unpacked Dimension | |
| mm | : 168 x 72 x 18.5 |
| inches | : 6.61" x 2.83" x 0.73" |
| Weight | |
| Power Bank | |
| Starting at 258 g (0.63 lbs) | |
| Packed | |
| Starting at 384 g (0.85 lbs) | |
| Power Buttons | |
| Short Press | |
| Activate and Battery Life Check | |
| LED Indicators | |
| 4 LED/Power Indicators | |
| 100% - 75% | : 4 LEDs |
| 75% - 50% | : 3 LEDs |
| 50% - 25% | : 2 LEDs |
| Lower 25% | : 1 LED |

CONNECTIVITY

| | |
|-------------------------------|--|
| Cable | |
| 433 mm USB-C Integrated Cable | |
| Cable Management | |
| Logo Pull to Release | |

INFORMATION

| | |
|---|--|
| Warranty | |
| 1 Year | |
| Ship Group (What's in the Box) | |
| Lenovo Go Wireless Mobile Power Bank | |
| Warranty Document | |
| Quick Start Manual | |
| Part Numbers (PN) | |
| Commercial (Thunder Black Color) | |
| 40ALLG1WWW | |
| Consumer (Storm Grey Color) | |
| GOA3LG1WWW | |

¹ Depends on power adapter used. Value measured using Lenovo 45W power adapter.

² 1 x USB-C integrated cable and 1 x USB-C port.



WWW.LENOVO.COM/GO

Lenovo reserves the right to alter product offerings and specifications at any time, without notice. Lenovo makes every effort to ensure accuracy of all information but is not liable or responsible for any editorial, photographic, or typographic errors. All images are for illustration purposes only. For full Lenovo product, service, and warranty specifications, visit www.lenovo.com. Lenovo makes no representations or warranties regarding third-party products or services. **Trademarks:** The following are trademarks or registered trademarks of Lenovo: Lenovo, the Lenovo logo, Rescue and Recovery, ThinkPad, ThinkCentre, ThinkStation, ThinkServer, ThinkVantage, and ThinkVision. Other company, product, and service names may be trademarks or service marks of others. Battery life (and recharge times) will vary based on many factors, including system settings and usage. Visit www.lenovo.com/lenovo/us/en/safecomp/ periodically for the latest information on safe and effective computing. ©2021 Lenovo. All rights reserved.

Lenovo

Lenovo
Go